

**Product Code:** CMA1840

**Description:** 13A 2 Gang Double Pole Switched Safety Shutter Socket Outlet With Outboard Rockers & Neons



### General Information

<b>Plate Dimensions (mm)</b>	146 (W) x 86 (H) x 9.5 (D)	
<b>Plate Fixing Centres - Horizontal (mm)</b>	120.6	
<b>Style</b>	Rounded Profile	
<b>Finish</b>	Polar White	
<b>Materials</b>	Front Plate & Rocker Switch: Urea Neon Lens: Polycarbonate Terminal Screws: Steel & Yellow Passivated Internal Busbars: Formed Pressed Brass	Rear Housing : Urea Terminals: Brass Contacts: Silver "on-lay" Copper / Brass Earth Strap: Mild Steel
<b>Anti Microbial Certified</b>	Yes	
<b>Rated Voltage (V~) (Ue)</b>	250	<b>Frequency (Hz)</b> 50
<b>Resistive Load Rating (A)</b>	13	
<b>Termination Type</b>	Screw	
<b>Terminal Size (mm)</b>	Ø5	<b>Terminal Torque Value (Nm)</b> 2
<b>Terminal Capacity - Solid (mm<sup>2</sup>)</b>	3 x 2.5 or 2 x 4	
<b>Double Pole Switch</b>	Yes	
<b>3 Pin Safety Shuttered</b>	Yes	
<b>Twin Earth Terminals</b>	Yes	
<b>Neon Indicator</b>	Yes	<b>Indicator Colour</b> Orange
<b>Minimum Back Box Depth (mm)</b>	25	
<b>Ingress Protection</b>	IP20	
<b>Operational Temperature (°C)</b>	-5 to +40	
<b>Warranty (Years)</b>	20	

**Standards** BS 1363-2

### Additional Information

For cleaning / polishing of products, use only a soft, dry, clean cloth. Ensure that the mains supply is isolated before commencing installation and refer to the circuit diagram with the relevant product. Bare earth cables must always be covered with appropriate sleeving and wired to the earth terminal. All white moulded accessories are manufactured using Urea Formaldehyde, which has similar inherent properties against enveloped and non-enveloped viruses. All products have been independently tested with 99.9% of enveloped viruses and 92% of non-enveloped viruses killed off whilst achieving a 99.9% kill rate across all four types of the strains of bacteria - MRSA, E-Coli, Salmonella, and Klebsiella Pneumoniae. The safety shutter will only fully open when all three BS 1363 plug-top pins engage correctly with the shutter. Inserting the earth pin alone will not open the live and neutral shutter like conventional socket shutters.